

CA06-2.1, CA08-2.1, CA10-2.1, CA14-1.1

Solar Charger Controllers



- Electronically regulated charging regime:
Boost and float charge
- Deep discharge protection
- PWM series regulation, no panel short circuit
- Integrated temperature compensation
- Fully electronically protected:
Panel surge voltage
Wrong polarity at panel or battery
Overload and short circuit at load
- 3 LED indications: Charge Status, SOC, LVD,
Overload/Short Circuit
- Common positive allows grounding

The new version of CA solar charge controller series is especially designed for small solar systems with the need of a low battery disconnect feature.

Main differences to the preceding CA series:

The regulation circuit provides now series regulation to prevent single cell overheating problems of short-circuited solar panels.

The terminal section has been replaced by a rugged, well proven 16 mm² terminal block.

The melting fuse of the predecessor has been replaced by a fully electronically protected circuit.

2 LEDs and 1 Duo-LED to display charging in progress, battery SOC, load disconnect and overload status.

Leisure and rural electrification systems are the typical applications for this product. It is a perfect solution for cost-sensitive systems which require state-of-the-art system management.

The compact case is now similar to the well-known CML series.

Type	CA06-2.1	CA08-2.1	CA10-2.1	CA14-1.1
Normal Voltage	12V	12V	12V	12V
Max. module current	5A	8A	10A	14A
Max. load current	6A	8A	10A	14A
Self power consumption	4mA	4mA	4mA	4mA
Temperature compensation	-3mV/cell*°K	-3mV/cell*°K	-3mV/cell*°K	-3mV/cell*°K
Max.wire size	16mm ²	16mm ²	16mm ²	16mm ²
Temperature range	-40 to +50 °C	-40 to +50 °C	-40 to +50 °C	-40 to +50 °C
Dimensions	180 x 100 x 32mm	180 x 100 x 32mm	180 x 100 x 32mm	180 x 100 x 32mm
Weight	180gr	180gr	180gr	180gr
Type of protection	IP22	IP22	IP22	IP22

Phocos AG, Germany
info@phocos.com

Phocos China Ltd., China
Info-china@phocos.com

Phocos India Solar Pvt. Ltd., India
Info-india@phocos.com

Phocos Latin America S.R.L., Bolivia
Info-latinamerica@phocos.com

Phocos Rep. Office Australia, Australia
Info-australia@phocos.com

Phocos Rep. Office Brazil, Brazil
Info-brazil@phocos.com

Phocos Rep. Office Eastern Africa, Kenya
Info-easternafrica@phocos.com

Phocos Eastern Europe S.R.L., Romania
Info-easterneurope@phocos.com

Phocos SEA Pte Ltd, Singapore
Info-sea@phocos.com

Phocos Rep. Office South Africa
Info-sadc@phocos.com

Phocos Tunisia
Info-maghreb@phocos.com

Phocos USA
Info-usa@phocos.com